



Agilent 33220A 20 MHz Function/Arbitrary Waveform Generator

Data Sheet

- 20 MHz Sine and Square waveforms
- Pulse, Ramp, Triangle, Noise, and DC waveforms
- 14-bit, 50 MSa/s, 64 K-point Arbitrary waveforms
- AM, FM, PM, FSK, and PWM modulation types
- Linear & logarithmic sweeps and burst operation
- 10 mV_{pp} to 10 V_{pp} amplitude range
- Graph mode for visual verification of signal settings
- Connect via USB, GPIB and LAN

Uncompromising performance for functions and waveforms

The Agilent Technologies 33220A Function/Arbitrary Waveform Generator uses direct digital synthesis (DDS) techniques to create a stable, accurate output signal for clean, low distortion sine waves. It also gives you square waves with fast rise and fall times up to 20 MHz and linear ramp waves up to 200 kHz.

Pulse generation

The 33220A can generate variable-edge-time pulses up to 5 MHz. With variable period, pulse width, and amplitude the 33220A is ideally suited to a wide variety of applications requiring a flexible pulse signal.

Custom waveform generation

Use the 33220A to generate complex custom waveforms. With 14-bit resolution, and a sampling rate of 50 MSa/s, the 33220A gives you the flexibility to create the waveforms you need. It also lets you store up to four waveforms in nonvolatile memory.

The Agilent IntuiLink Arbitrary Waveform software allows you to easily create, edit, and download complex waveforms using the waveform editor. Or you can capture a waveform using IntuiLink for Oscilloscope and send it to the 33220A for output. To find out more about IntuiLink, visit www.agilent.com/find/intuilink.

Easy-to-use functionality

Front-panel operation of the 33220A is straightforward and user friendly. You can access all major functions with a single key or two. The knob or



numeric keypad can be used to adjust frequency, amplitude, offset, and other parameters. You can even enter voltage values directly in V_{pp}, V_{rms}, dBm, or as high and low levels. Timing parameters can be entered in Hertz (Hz) or seconds.

Internal AM, FM, PM, FSK, and PWM modulation make it easy to modulate waveforms without the need for a separate modulation source. Linear and logarithmic sweeps are also built in, with sweep rates selectable from 1 ms to 500 s. Burst mode operation allows for a user-selected number of cycles per period of time. GPIB, LAN, and USB interfaces are all standard, plus you get full programmability using SCPI commands.

External frequency reference (Option 001)

The 33220A external frequency reference lets you synchronize to an external 10 MHz clock, to another 33220A, or to an Agilent 33250A. Phase adjustments can be made from the front panel or via a computer interface, allowing precise phase calibration and adjustment.

WAVEFORMS

Standard	Sine, Square, Ramp, Triangle, Pulse, Noise, DC
Built-in arbitrary	Exponential rise, Exponential fall, Negative ramp, Sin(x)/x, Cardiac

WAVEFORM CHARACTERISTICS**Sine**

Frequency Range	1 μ Hz to 20 MHz	
Amplitude Flatness ^{[1],[2]} (relative to 1 kHz)	< 100 kHz	0.1 dB
	100 kHz to 5 MHz	0.15 dB
	5 MHz to 20 MHz	0.3 dB

Harmonic distortion ^{[2],[3]}	< 1 V _{PP}	\geq 1 V _{PP}
DC to 20 kHz	-70 dBc	-70 dBc
20 kHz to 100 kHz	-65 dBc	-60 dBc
100 kHz to 1 MHz	-50 dBc	-45 dBc
1 MHz to 20 MHz	-40 dBc	-35 dBc

Total harmonic distortion ^{[2],[3]}	DC to 20 kHz	0.04%
--	--------------	-------

Spurious (non-harmonic) ^{[2],[4]}	DC to 1 MHz	-70 dBc
	1 MHz to 20 MHz	-70 dBc + 6 dB/octave

Phase noise (10 kHz offset)	-115 dBc / Hz, typical
-----------------------------	------------------------

Square

Frequency range	1 μ Hz to 20 MHz
Rise/Fall time	< 13 ns
Overshoot	< 2%
Variable duty cycle	20% to 80% (to 10 MHz) 40% to 60% (to 20 MHz)

Asymmetry (@ 50% duty)	1% of period + 5 ns
Jitter (RMS)	1 ns + 100 ppm of period

Ramp, Triangle

Frequency range	1 μ Hz to 200 kHz
Linearity	< 0.1% of peak output
Variable Symmetry	0.0% to 100.0%

Pulse

Frequency range	500 μ Hz to 5 MHz
Pulse width (period \leq 10s)	20 ns minimum, 10 ns resolution
Variable edge time	< 13 ns to 100 ns
Overshoot	< 2%
Jitter (RMS)	300 ps + 0.1 ppm of period

Noise

Bandwidth	10 MHz typical
-----------	----------------

Arbitrary

Frequency range	1 μ Hz to 6 MHz
Waveform length	2 to 64 K points
Amplitude resolution	14 bits (including sign)
Sample rate	50 MSa/s
Min. Rise/Fall Time	35 ns typical
Linearity	< 0.1% of peak output
Settling Time	< 250 ns to 0.5% of final value
Jitter (RMS)	6 ns + 30 ppm
Non-volatile memory	four waveforms

COMMON CHARACTERISTICS**Frequency**

Resolution	1 μ Hz
------------	------------

Amplitude

Range	10 mV _{PP} to 10 V _{PP} into 50 Ω 20 mV _{PP} to 20 V _{PP} into open circuit
-------	---

Accuracy ^{[1],[2]} (at 1 kHz)	\pm 1% of setting \pm 1 mV _{PP}
--	--

Units	V _{PP} , V _{rms} , dBm
-------	--

Resolution	4 digits
------------	----------

DC Offset

Range (peak AC + DC)	\pm 5 V into 50 Ω \pm 10 V into open circuit
----------------------	--

Accuracy ^{[1],[2]}	\pm 2% of offset setting \pm 0.5% of amplitude \pm 2 mV
-----------------------------	--

Resolution	4 digits
------------	----------

Main Output

Impedance	50 Ω typical
-----------	---------------------

Isolation	42 Vpk maximum to earth
-----------	-------------------------

Protection	Short-circuit protected, overload automatically disables main output
------------	--

Internal Frequency Reference

Accuracy ^[5]	\pm 10 ppm in 90 days \pm 20 ppm in 1 year
-------------------------	---

External Frequency Reference (Option 001)**Rear Panel Input**

Lock Range	10 MHz \pm 500 Hz
------------	---------------------

Level	100 mV _{PP} to 5 V _{PP}
-------	---

Impedance	1 k Ω typical, AC coupled
-----------	----------------------------------

Lock Time	< 2 seconds
-----------	-------------

Rear Panel Output

Frequency	10 MHz
-----------	--------

Level	632 mV _{PP} (0 dBm), typical
-------	---------------------------------------

Impedance	50 Ω typical, AC coupled
-----------	---------------------------------

Phase Offset

Range	+ 360 $^\circ$ to - 360 $^\circ$
-------	----------------------------------

Resolution	0.001 $^\circ$
------------	----------------

Accuracy	20 ns
----------	-------

MODULATION**AM**

Carrier waveforms	Sine, Square, Ramp, Arb
-------------------	-------------------------

Source	Internal/External
--------	-------------------

Internal modulation	Sine, Square, Ramp, Triangle, Noise, Arb (2 mHz to 20 kHz)
---------------------	--

Depth	0.0% to 120.0%
-------	----------------

FM

Carrier waveforms	Sine, Square, Ramp, Arb
-------------------	-------------------------

Source	Internal/External
--------	-------------------

Internal modulation	Sine, Square, Ramp, Triangle, Noise, Arb (2 mHz to 20 kHz)
---------------------	--

Deviation	DC to 10 MHz
-----------	--------------

PM

Carrier waveforms	Sine, Square, Ramp, Arb
-------------------	-------------------------

Source	Internal/External
--------	-------------------

Internal modulation	Sine, Square, Ramp, Triangle, Noise, Arb (2 mHz to 20 kHz)
---------------------	--

Deviation	0.0 to 360.0 degrees
-----------	----------------------

PWM

Carrier waveform	Pulse
Source	Internal/External
Internal modulation	Sine, Square, Ramp, Triangle, Noise, Arb (2 MHz to 20 kHz)
Deviation	0% to 100% of pulse width

FSK

Carrier waveforms	Sine, Square, Ramp, Arb
Source	Internal/External
Internal modulation	50% duty cycle square (2 MHz to 100 kHz)

External Modulation Input⁽⁶⁾ (for AM, FM, PM, PWM)

Voltage range	± 5 V full scale
Input impedance	5 kΩ typical
Bandwidth	DC to 20 kHz

SWEEP

Waveforms	Sine, Square, Ramp, Arb
Type	Linear or Logarithmic
Direction	Up or Down
Sweep time	1 ms to 500 s
Trigger	Single, External, or Internal
Marker	falling edge of sync signal (programmable frequency)

BURST⁽⁷⁾

Waveforms	Sine, Square, Ramp, Triangle, Pulse, Noise, Arb
Type	Counted (1 to 50,000 cycles), Infinite, Gated
Start/Stop Phase	-360° to +360°
Internal Period	1 μs to 500 s
Gate Source	External trigger
Trigger source	Single, External or Internal

TRIGGER CHARACTERISTICS

Trigger input	
Input level	TTL compatible
Slope	Rising or Falling, selectable
Pulse width	> 100 ns
Input impedance	>10 kΩ, DC coupled
Latency	< 500 ns
Jitter (rms)	6 ns (3.5 ns for pulse)
Trigger output	
Level	TTL compatible into ≥ 1 kΩ
Pulse width	> 400 ns
Output Impedance	50 Ω, typical
Maximum rate	1 MHz
Fanout	≤ 4 Agilent 33220As

PROGRAMMING TIMES (typical)

Configuration times			
	USB	LAN	GPIB
Function Change	111 ms	111 ms	111 ms
Frequency Change	1.5 ms	2.7 ms	1.2 ms
Amplitude Change	30 ms	30 ms	30 ms
Select User Arb	124 ms	124 ms	123 ms
Arb Download Times (binary transfer)			
	USB	LAN	GPIB
64K points	96.9 ms	191.7 ms	336.5 ms
16K points	24.5 ms	48.4 ms	80.7 ms
4K points	7.3 ms	14.6 ms	19.8 ms

GENERAL

Power Supply	CAT II 100 - 240V @ 50/60Hz (-5%, +10%) 100 - 120V @ 400Hz (±10%)
Power Consumption	50 VA max
Operating Environment	IEC 61010 Pollution Degree 2 Indoor Location
Operating Temperature	0°C to 55°C
Operating Humidity	5% to 80% RH, non-condensing
Operating Altitude	Up to 3000 meters
Storage Temperature	-30°C to 70°C
State Storage Memory	Power off state automatically saved. Four user-configurable stored states
Interface	USB, GPIB, and LAN standard
Language	SCPI - 1993, IEEE-488.2
Dimensions (W x H x D)	
Bench top	261.1mm x 103.8mm x 303.2mm
Rack mount	212.8mm x 88.3mm x 272.3mm
Weight	3.4 kg (7.5 lbs)
Safety Designed to	UL-1244, CSA 1010, EN61010
EMC Tested to	MIL-461C, EN55011, EN50082-1
Vibration and Shock	MIL-T-28800, Type III, Class 5
Acoustic Noise	30 dBa
Warm-up Time	1 hour
Warranty	1 year

Footnotes

⁽¹⁾ add 1/10th of output amplitude and offset spec per °C for operation outside the range of 18°C to 28°C

⁽²⁾ Autorange enabled

⁽³⁾ DC offset set to 0 V

⁽⁴⁾ spurious output at low amplitude is -75 dBm typical

⁽⁵⁾ add 1 ppm/°C average for operation outside the range of 18°C to 28°C

⁽⁶⁾ FSK uses trigger input (1 MHz maximum)

⁽⁷⁾ Sine and square waveforms above 6 MHz are allowed only with an "infinite" burst count

Agilent Technologies' Test and Measurement Support, Services, and Assistance

Agilent Technologies aims to maximize the value you receive, while minimizing your risk and problems. We strive to ensure that you get the test and measurement capabilities you paid for and obtain the support you need. Our extensive support resources and services can help you choose the right Agilent products for your applications and apply them successfully. Every instrument and system we sell has a global warranty. Support is available for at least five years beyond the production life of the product. Two concepts underlie Agilent's overall support policy: "Our Promise" and "Your Advantage."

Our Promise

Our Promise means your Agilent test and measurement equipment will meet its advertised performance and functionality. When you are choosing new equipment, we will help you with product information, including realistic performance specifications and practical recommendations from experienced test engineers. When you use Agilent equipment, we can verify that it works properly, help with product operation, and provide basic measurement assistance for the use of specified capabilities, at no extra cost upon request. Many self-help tools are available.

Your Advantage

Your Advantage means that Agilent offers a wide range of additional expert test and measurement services, which you can purchase according to your unique technical and business needs. Solve problems efficiently and gain a competitive edge by contracting with us for calibration, extra-cost upgrades, out-of-warranty repairs, and on-site education and training, as well as design, system integration, project management, and other professional engineering services. Experienced Agilent engineers and technicians worldwide can help you maximize your productivity, optimize the return on investment of your Agilent instruments and systems, and obtain dependable measurement accuracy for the life of those products.



Agilent Email Updates

www.agilent.com/find/emailupdates

Get the latest information on the products and applications you select.

Agilent T&M Software and Connectivity

Agilent's Test and Measurement software and connectivity products, solutions and developer network allows you to take time out of connecting your instruments to your computer with tools based on PC standards, so you can focus on your tasks, not on your connections.

Visit www.agilent.com/find/connectivity for more information.

By internet, phone, or fax, get assistance with all your test & measurement needs

Online assistance:

www.agilent.com/find/assist

Phone or Fax

United States:

(tel) 800 829 4444

Canada:

(tel) 877 894 4414

(fax) 905 282 6495

China:

(tel) 800 810 0189

(fax) 800 820 2816

Europe:

(tel) (31 20) 547 2323

(fax) (31 20) 547 2390

Japan:

(tel) (81) 426 56 7832

(fax) (81) 426 56 7840

Korea:

(tel) (82 2) 2004 5004

(fax) (82 2) 2004 5115

Latin America:

(tel) (305) 269 7500

(fax) (305) 269 7599

Taiwan:

(tel) 0800 047 866

(fax) 0800 286 331

Other Asia Pacific Countries:

(tel) (65) 6375 8100

(fax) (65) 6836 0252

(e-mail) tm_asia@agilent.com

Product specifications and descriptions in this document subject to change without notice.

© Agilent Technologies, Inc. 2003, 2004

Printed in the USA May 1, 2004

5988-8544EN

